# Product data sheet Characteristics

## SUVTP10KH2B2S

APC Smart-UPS VT 10kVA 400V w/2 Batt Mod., Start-Up 5X8, Int Maint Bypass, Parallel Capable



## Commercial status

Discontinued on: 14 January 2021

To be end-of-service on: 31 December 2030

#### Overview Lead time

General		
Provided equipment	Battery modules ship installed CD with software Network management card Smart UPS signalling RS-232 cable User manual Bolt down brackets Installation guide Start up included	
Performance multiplier	1	
Number of tare power	180 W	
Number of power module free slots	0	
Number of power module filled slots	0	
Redundant	No	
Size UPS version	Internetworking Server Telecom	:
UPS size	L	
Value multiplier	1	

Usually Ships within 2 Weeks

#### Physical

Colour	Black	
Depth	84.2 cm	
Height	149 cm	- V
Mounting location	Front	9
Mounting preference	No preference	<u>.</u>
Net weight	396.82 kg	9
Mounting mode	Not rack-mountable	
Two post mountable	0	9
USB compatible	No	
Width	35.2 cm	F

## Input

Network frequency	4070 Hz auto-sensing	
Number of input connectors	1 hard wire 5-wire (3P + N + E)	
Input voltage limits	304477 V	
Inputvolt_other	380 V 415 V	
Maximum input current	14 A	
Switching current capacity	20 A	
Input voltage	400 V 3 phases	
Cos phi	0.98	

## Output

Ration power in W         8000 W           Maximum configurable power in W         8000 W           Harmonic distortion         Less than 5 % at full load           Output frequency         4753 Hz for 50 Hz nominal sync to mains 50 Hz +/- 0.1 % for 50 Hz nominal sync to mains 50 Hz +/- 0.1 % for 50 Hz nominal unsynctronised           Outputvol_other         380 V	Output	
Harmonic distortion         Less than 5 % at full load           Output frequency         4753 Hz for 50 Hz nominal sync to mains 50 Hz +/- 0.1 % for 50 Hz nominal unsynchronised           Output/oit_other         380 V 415 V           Crest factor         3 : 1           UPS type         Double conversion online           Wave type         Sine wave           Connections - terminals         1 screw terminals           Output connector type         Hard wire 4-wire (3P + E) 1 Hard wire 4-wire (3P + N + E) 1           Bypass type         Bull-tin maintenance bypass Bull-tin static bypass           Curve equation         Efficiency           Curve load maximum         100 %           Curve load maximum         100 %           Curve proportional loss         0.0213           Curve square loss         0.0205           Curve Exaxis maximum         100 %           Curve Exaxis minimum         0 %           Curve X-axis minimum         0 %           Curve X-axis minimum         0 %           Curve X-axis title         Load           Curve Y-axis title         Load           Curve Y-axis minimum         100 %           Curve Y-axis minimum         50 %           Curve Y-axis title         Efficiency	Rated power in W	8000 W
Output frequency 4753 Hz for 50 Hz nominal sync to mains 50 Hz +/- 0.1 % for 50 Hz nominal unsynchronised  Outputvolt_other 380 V 415 V  Crest factor 3:1  UPS type Double conversion online  Wave type Sine wave  Connections - terminals 1 screw terminals  Output connector type Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + E) 1 Har	Maximum configurable power in W	8000 W
S0 Hz +/- 0.1 % for 50 Hz nominal unsynchronised           Output/oil_ other         380 V 415 V           Crest factor         3 : 1           UPS type         Double conversion online           Wave type         Sine wave           Connections - terminals         1 screw terminals           Output connector type         Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + N + E) 1           Bypass type         Built-in maintenance bypass Built-in static bypass           Curve equation         Efficiency           Curve load maximum         100 %           Curve load maximum         2 %           Curve load minimum         2 %           Curve proportional loss         0.0211           Curve square loss         0.0205           Curve Est cond ID         Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with norminal electrical input and balanced PF = 0.8 output.           Curve X-axis minimum         0 %           Curve X-axis title         Load           Curve Y-axis minimum         100 %           Curve Y-axis minimum         50 % <t< td=""><td>Harmonic distortion</td><td>Less than 5 % at full load</td></t<>	Harmonic distortion	Less than 5 % at full load
Crest factor         3 : 1           UPS type         Double conversion online           Wave type         Sine wave           Connections - terminals         1 screw terminals           Output connector type         Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + N + E) 1           Bypass type         Built-in maintenance bypass Built-in static bypass           Curve equation         Efficiency           Curve fixed loss         0.0123           Curve load maximum         100 %           Curve load minimum         2 %           Curve square loss         0.0211           Curve x-axis maximum         100 %           Curve test cond ID         Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.           Curve X-axis minimum         0 %           Curve X-axis minimum         0 %           Curve X-axis minimum         0 %           Curve Y-axis maximum         100 %           Curve Y-axis minimum         50 %           Curve Y-axis minimum         50 %           Curve Y-axis minimum         60 %           Curve Y-axis minimum         100 %           Curve Y-axis minimum         60 %           Curve Y-ax	Output frequency	
UPS type         Double conversion online           Wave type         Sine wave           Connections - terminals         1 screw terminals           Output connector type         Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + N + E) 1           Bypass type         Built-in maintenance bypass Built-in static bypass           Curve equation         Efficiency           Curve fixed loss         0.0123           Curve load maximum         100 %           Curve load minimum         2 %           Curve proportional loss         0.0211           Curve square loss         0.0205           Curve X-axis maximum         100 %           Curve St cond ID         Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.           Curve X-axis minimum         0 %           Curve X-axis units         Percentage           Curve Y-axis minimum         50 %           Curve Y-axis minimum         50 %           Curve Y-axis units         Percentage           Curve Y-axis units         Percentage           Curve Y-axis units         Percentage           Curve Y-axis units         Percentage           Curve Y-axis units         Percentage </td <td>Outputvolt_other</td> <td></td>	Outputvolt_other	
Wave type Sine wave  Connections - terminals 1 screw terminals  Output connector type Hard wire 4-wire (3P + E) 1 Hard wire 4-wire (3P + N + E) 1  Bypass type Built-in maintenance bypass Built-in static bypass  Built-in maintenance bypass Built-in static bypass  Curve equation Efficiency  Curve load maximum 100 %  Curve load maximum 2 %  Curve load minimum 2 %  Curve load minimum 2 %  Curve square loss 0.0211  Curve square loss 0.0205  Curve X-axis maximum 100 %  Curve test cond ID Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum 0 %  Curve X-axis inimum 100 %  Curve X-axis units Percentage  Curve Y-axis maximum 100 %  Curve Y-axis minimum 50 %  Curve Y-axis units Percentage	Crest factor	3:1
Connections - terminals     1 screw terminals       Output connector type     Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + N + E) 1       Bypass type     Built-in maintenance bypass Built-in static bypass       Curve equation     Efficiency       Curve load maximum     100 %       Curve load minimum     2 %       Curve propritional loss     0.0211       Curve square loss     0.0205       Curve test cond ID     Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.       Curve X-axis minimum     0 %       Curve X-axis units     Percentage       Curve Y-axis maximum     100 %       Curve Y-axis minimum     50 %       Curve Y-axis units     Percentage       Curve Y-axis units     Percentage       Graph display     1       Maximum output current     16 A       Output voltage     400 V 3 phases       Maximum configurable power in VA     10000 VA	UPS type	Double conversion online
Output connector type     Hard wire 4-wire (3P + E) 1 Hard wire 5-wire (3P + N + E) 1       Bypass type     Built-in maintenance bypass Built-in static bypass       Curve equation     Efficiency       Curve fixed loss     0.0123       Curve load maximum     100 %       Curve load minimum     2 %       Curve proportional loss     0.0211       Curve square loss     0.0205       Curve X-axis maximum     100 %       Curve test cond ID     Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.       Curve X-axis minimum     0 %       Curve X-axis units     Percentage       Curve Y-axis maximum     100 %       Curve Y-axis minimum     50 %       Curve Y-axis minimum     50 %       Curve Y-axis units     Percentage       Graph display     1       Maximum output current     16 A       Output voltage     400 V 3 phases       Maximum configurable power in VA     10000 VA	Wave type	Sine wave
Hard wire 5-wire (3P + N + E) 1  Bypass type  Built-in maintenance bypass Built-in static bypass  Curve equation  Efficiency  Curve fixed loss  0.0123  Curve load maximum  100 %  Curve load minimum  2 %  Curve proportional loss  0.0211  Curve square loss  0.0205  Curve X-axis maximum  100 %  Curve test cond ID  Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum  0 %  Curve X-axis units  Percentage  Curve Y-axis units  Percentage  Curve Y-axis minimum  50 %  Curve Y-axis units  Percentage  Graph display  1  Maximum output current  16 A  Output voltage  Maximum configurable power in VA  10000 VA	Connections - terminals	1 screw terminals
Curve equation       Efficiency         Curve fixed loss       0.0123         Curve load maximum       100 %         Curve load minimum       2 %         Curve proportional loss       0.0211         Curve square loss       0.0205         Curve X-axis maximum       100 %         Curve test cond ID       Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.         Curve X-axis minimum       0 %         Curve X-axis title       Load         Curve Y-axis units       Percentage         Curve Y-axis maximum       100 %         Curve Y-axis minimum       50 %         Curve Y-axis title       Efficiency         Curve Y-axis units       Percentage         Curve Y-axis units       Percentage         Graph display       1         Maximum output current       16 A         Output voltage       400 V 3 phases         Maximum configurable power in VA       10000 VA	Output connector type	
Curve fixed loss 0.0123 Curve load maximum 100 % Curve load minimum 2 % Curve proportional loss 0.0211 Curve square loss 0.0205 Curve X-axis maximum 100 % Curve test cond ID Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output. Curve X-axis minimum 0 % Curve X-axis minimum 0 % Curve X-axis title Load Curve X-axis units Percentage Curve Y-axis maximum 100 % Curve Y-axis minimum 50 % Curve Y-axis minimum 50 % Curve Y-axis minimum Fercentage Curve Y-axis minimum 50 % Curve Y-axis units Percentage Graph display 1 Maximum output current 16 A Output voltage 400 V 3 phases Maximum configurable power in VA 10000 VA	Bypass type	
Curve load maximum 100 %  Curve load minimum 2 %  Curve proportional loss 0.0211  Curve square loss 0.0205  Curve X-axis maximum 100 %  Curve test cond ID Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum 0 %  Curve X-axis minimum 0 %  Curve X-axis units Percentage  Curve Y-axis maximum 100 %  Curve Y-axis maximum 100 %  Curve Y-axis minimum 50 %  Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve equation	Efficiency
Curve load minimum       2 %         Curve proportional loss       0.0211         Curve square loss       0.0205         Curve X-axis maximum       100 %         Curve test cond ID       Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.         Curve X-axis minimum       0 %         Curve X-axis units       Percentage         Curve Y-axis maximum       100 %         Curve Y-axis minimum       50 %         Curve Y-axis title       Efficiency         Curve Y-axis units       Percentage         Graph display       1         Maximum output current       16 A         Output voltage       400 V 3 phases         Maximum configurable power in VA       10000 VA	Curve fixed loss	0.0123
Curve proportional loss       0.0211         Curve square loss       0.0205         Curve X-axis maximum       100 %         Curve test cond ID       Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.         Curve X-axis minimum       0 %         Curve X-axis units       Percentage         Curve Y-axis maximum       100 %         Curve Y-axis minimum       50 %         Curve Y-axis title       Efficiency         Curve Y-axis units       Percentage         Graph display       1         Maximum output current       16 A         Output voltage       400 V 3 phases         Maximum configurable power in VA       10000 VA	Curve load maximum	100 %
Curve square loss 0.0205  Curve X-axis maximum 100 %  Curve test cond ID Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum 0 %  Curve X-axis title Load  Curve X-axis units Percentage  Curve Y-axis maximum 100 %  Curve Y-axis minimum 50 %  Curve Y-axis title Efficiency  Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve load minimum	2 %
Curve X-axis maximum  Curve test cond ID  Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum  0 %  Curve X-axis title  Load  Curve X-axis units  Percentage  Curve Y-axis maximum  100 %  Curve Y-axis minimum  50 %  Curve Y-axis title  Efficiency  Curve Y-axis units  Percentage  Graph display  1  Maximum output current  16 A  Output voltage  400 V 3 phases  Maximum configurable power in VA  10000 VA	Curve proportional loss	0.0211
Curve test cond ID  Curve fit to measured efficiency data. All measurements taken in normal operating mode, at typical environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum  0 %  Curve X-axis title  Load  Curve X-axis units  Percentage  Curve Y-axis maximum  100 %  Curve Y-axis minimum  50 %  Curve Y-axis title  Efficiency  Curve Y-axis units  Percentage  Graph display  1  Maximum output current  16 A  Output voltage  400 V 3 phases  Maximum configurable power in VA  10000 VA	Curve square loss	0.0205
environmental conditions, with nominal electrical input and balanced PF = 0.8 output.  Curve X-axis minimum  0 %  Curve X-axis title  Load  Curve X-axis units  Percentage  Curve Y-axis maximum  100 %  Curve Y-axis minimum  50 %  Curve Y-axis title  Efficiency  Curve Y-axis units  Percentage  Graph display  1  Maximum output current  16 A  Output voltage  Maximum configurable power in VA  10000 VA	Curve X-axis maximum	100 %
Curve X-axis title  Curve X-axis units  Percentage  Curve Y-axis maximum  100 %  Curve Y-axis minimum  50 %  Curve Y-axis title  Efficiency  Curve Y-axis units  Percentage  Graph display  1  Maximum output current  16 A  Output voltage  400 V 3 phases  Maximum configurable power in VA  10000 VA	Curve test cond ID	
Curve X-axis units Percentage  Curve Y-axis maximum 100 %  Curve Y-axis minimum 50 %  Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve X-axis minimum	0 %
Curve Y-axis maximum 100 %  Curve Y-axis minimum 50 %  Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve X-axis title	Load
Curve Y-axis minimum 50 %  Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve X-axis units	Percentage
Curve Y-axis title Efficiency  Curve Y-axis units Percentage  Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve Y-axis maximum	100 %
Curve Y-axis units Percentage Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve Y-axis minimum	50 %
Graph display 1  Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve Y-axis title	Efficiency
Maximum output current 16 A  Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Curve Y-axis units	Percentage
Output voltage 400 V 3 phases  Maximum configurable power in VA 10000 VA	Graph display	1
Maximum configurable power in VA 10000 VA	Maximum output current	16 A
	Output voltage	400 V 3 phases
Rated power in VA 10000 VA	Maximum configurable power in VA	10000 VA
	Rated power in VA	10000 VA

## Conformance

Product certifications	C-Tick	
	CE	
	RCM	

EN 50091-2	
EN/IEC 62040-3	
IEC 61000-3-2	
IEC 61000-3-3	
ISO 14001	
ISO 9001	
VFI-SS-111	
	EN/IEC 62040-3 IEC 61000-3-2 IEC 61000-3-3 ISO 14001 ISO 9001

### Environmental

Ambient air temperature for operation	040 °C
Relative humidity	095 %
Operating altitude	03333 ft
Ambient air temperature for storage	-5040 °C
Storage Relative Humidity	095 %
Storage altitude	0.0015240.00 m
Acoustic level	64 dBA
Heat dissipation	1774 Btu/h
Show note OP temperature	No
IP degree of protection	IP20

### Batteries & Runtime

Battery type	VRLA	
Number of battery filled slots	2	
•		
Number of battery free slots	0	
Battery recharge time	5 h	
Number of battery replacement quantity	2	
Additional information	Configurable for 380 : 400 or 415 V 3 Phase nominal output voltage	
Liquid value	0	
Battery voltage	+/- 192 V (split battery referenced to neutral)	
Discharge battery voltage	+/- 154 V	
Battery curve	В	
Battery charger power	995 W rated	
Battery power in VAH	4983 VAh runtime	
Battery life	35 year(s)	
Battery option	SUVTXR2B6S 1 9899 VAh SUVTXR6B6S 1 19687 VAh SUVTXR6B6S 2 34762 VAh SUVTXR6B6S 3 49936 VAh SUVTXR6B6S 4 65348 VAh	
Battery graph comments	Estimated runtimes based on battery vendor data, at typical environmental conditions, with no electrical input and balanced PF = 0.8 output.	
Extended runtime	1	

#### Communications & Management

Free slots	0	
Preinstalled device	Network management card 2 with environmental monitoring	
Control panel	Multifunction LCD status and control console	
Alarm	Audible and visible alarms prioritized by severity	
Emergency power off	Yes	

## Packing Units

<u> </u>		
Package 1 Weight	427.73 kg	
Package 1 Height	164.3 cm	
Package 1 width	65 cm	

Package 1 Length	106.2 cm	
Number of Units in Package 3	1	
Offer Sustainability		
EU RoHS Directive	Under investigation	
Contractual warranty		

1 year repair or replace, Start-Up Service

Warranty