

# TPS563210EVM-663 3-A, Regulator Evaluation Module

This user's guide contains information for the TPS563210 as well as support documentation for the TPS563210EVM-663 evaluation module. Included are the performance specifications, schematic, and the bill of materials of the TPS563210EVM-663.

## Contents

|      |   |    |
|------|---|----|
| 1    | Introduction .....                                | 2  |
| 2    | Performance Specification Summary .....           | 2  |
| 3    | Modifications.....                                | 3  |
| 3.1  | Output Voltage Setpoint.....                      | 3  |
| 4    | Test Setup and Results .....                      | 4  |
| 4.1  | Input/Output Connections.....                     | 4  |
| 4.2  | Start-Up Procedure .....                          | 4  |
| 4.3  | Efficiency.....                                   | 5  |
| 4.4  | Load Regulation.....                              | 6  |
| 4.5  | Line Regulation .....                             | 7  |
| 4.6  | Load Transient Response .....                     | 7  |
| 4.7  | Output Voltage Ripple.....                        | 8  |
| 4.8  | Input Voltage Ripple .....                        | 9  |
| 4.9  | Start-Up.....                                     | 10 |
| 4.10 | Shut-Down .....                                   | 11 |
| 5    | Board Layout.....                                 | 12 |
| 5.1  | Layout.....                                       | 12 |
| 6    | Schematic, Bill of Materials, and Reference ..... | 13 |
| 6.1  | Schematic .....                                   | 13 |
| 6.2  | Bill of Materials .....                           | 14 |
| 6.3  | Reference .....                                   | 15 |

## List of Figures

|    |   |    |
|----|---|----|
| 1  | TPS563210EVM-663 Efficiency .....                                       | 5  |
| 2  | TPS563210EVM-663 Light Load Efficiency .....                            | 5  |
| 3  | TPS563210EVM-663 Load Regulation, 5 V Input.....                        | 6  |
| 4  | TPS563210EVM-663 Load Regulation, 12 V Input .....                      | 6  |
| 5  | TPS563210EVM-663 Line Regulation .....                                  | 7  |
| 6  | TPS563210EVM-663 Load Transient Response, 25% to 75% Load Step.....     | 7  |
| 7  | TPS563210EVM-663 Output Voltage Ripple, $I_{OUT} = 3\text{ A}$ .....    | 8  |
| 8  | TPS563210EVM-663 Output Voltage Ripple, $I_{OUT} = 300\text{ mA}$ ..... | 8  |
| 9  | TPS563210EVM-663 Output Voltage Ripple, $I_{OUT} = 0\text{ mA}$ .....   | 9  |
| 10 | TPS563210EVM-663 Input Voltage Ripple, $I_{OUT} = 3\text{ A}$ .....     | 9  |
| 11 | TPS563210EVM-663 Start-Up Relative to $V_{IN}$ .....                    | 10 |
| 12 | TPS563210EVM-663 Start-Up Relative to EN .....                          | 10 |
| 13 | TPS563210EVM-663 Shut-Down Relative to $V_{IN}$ .....                   | 11 |
| 14 | TPS563210EVM-663 Shut-Down Relative to EN .....                         | 11 |
| 15 | Top Assembly.....   | 12 |

D-CAP2 is a trademark of Texas Instruments.

|    |   |    |
|----|---|----|
| 16 | Top Layer.....                          | 12 |
| 17 | Bottom Layer.....                       | 13 |
| 18 | TPS563210EVM-663 Schematic Diagram..... | 13 |

### List of Tables

|   |  |    |
|---|--|----|
| 1 | Input Voltage and Output Current Summary.....            | 2  |
| 2 | TPS563210EVM-663 Performance Specifications Summary..... | 2  |
| 3 | Output Voltages.....                                     | 3  |
| 4 | Connection and Test Points.....                          | 4  |
| 5 | Bill of Materials.....                                   | 14 |

## 1 Introduction

The TPS563210 is a single, adaptive on-time, D-CAP2™ mode, synchronous buck converter requiring a very low external component count. The D-CAP2 control circuit is optimized for low-ESR output capacitors such as POSCAP, SP-CAP, or ceramic types and features fast transient response with no external compensation. The slow start time is externally programmable and there is a dedicated Power Good (PG) pin to aid in voltage monitoring and sequencing. The switching frequency is internally set at a nominal 650 kHz and enters advanced Eco-mode in light load conditions. The high-side and low-side switching MOSFETs are incorporated inside the TPS563210 package along with the gate-drive circuitry. The low drain-to-source on resistance of the MOSFETs allows the TPS563210 to achieve high efficiencies and helps keep the junction temperature low at high output currents. The TPS563210 dc/dc synchronous converter is designed to provide up to a 3-A output from an input voltage source of 4.5 V to 17 V. The output voltage range is from 0.8 V to 6.5 V. Rated input voltage and output current ranges for the evaluation module are given in [Table 1](#).

The TPS563210EVM-663 evaluation module (EVM) is a single, synchronous buck converter providing 1.05 V at 3 A from 4.5-V to 17-V input. This user's guide describes the TPS563210EVM-663 performance.

**Table 1. Input Voltage and Output Current Summary**

| EVM              | Input Voltage Range                       | Output Current Range |
|------------------|---|----------------------|
| TPS563210EVM-663 | $V_{IN} = 4.5 \text{ V to } 17 \text{ V}$ | 0 A to 3 A           |

## 2 Performance Specification Summary

A summary of the TPS563210EVM-663 performance specifications is provided in [Table 2](#). Specifications are given for an input voltage of  $V_{IN} = 12 \text{ V}$  and an output voltage of 1.05 V, unless otherwise noted. The ambient temperature is 25°C for all measurement, unless otherwise noted.

**Table 2. TPS563210EVM-663 Performance Specifications Summary**

| Specifications                   |                       | Test Conditions                                | Min | Typ  | Max | Unit             |
|----------------------------------|-----------------------|--|-----|------|-----|------------------|
| Input voltage range ( $V_{IN}$ ) |                       |  | 4.5 | 12   | 17  | V                |
| CH1                              | Output voltage        |  |     | 1.05 |     | V                |
|                                  | Operating frequency   | $V_{IN} = 12 \text{ V}, I_O = 3 \text{ A}$     |     | 650  |     | kHz              |
|                                  | Output current range  |  | 0   |      | 3   | A                |
|                                  | Over current limit    | $V_{IN} = 12 \text{ V}, L_O = 1.5 \mu\text{H}$ |     |      |     | A                |
|                                  | Output ripple voltage | $V_{IN} = 12 \text{ V}, I_O = 3 \text{ A}$     |     | 20   |     | mV <sub>pp</sub> |

### 3 Modifications

These evaluation modules are designed to provide access to the features of the TPS563210. Some modifications can be made to this module.

#### 3.1 Output Voltage Setpoint

To change the output voltage of the EVMs, it is necessary to change the value of resistor R1. Changing the value of R1 can change the output voltage above 0.765 V. The value of R1 for a specific output voltage can be calculated using [Equation 1](#).

$$R1 = \frac{R2 \times (V_{OUT} - 0.765 \text{ V})}{0.765 \text{ V}} \quad (1)$$

[Table 3](#) lists the R1 values for some common output voltages. Note that the values given in [Table 3](#) are standard values and not the exact value calculated using [Table 3](#).

**Table 3. Output Voltages**

| Output Voltage (V) | R1 (kΩ) | R2 (kΩ) | L1 (μH) |     |     | C5 + C6 + C7 (μF) |
|--------------------|---------|---------|---------|-----|-----|-------------------|
|                    |         |         | Min     | Typ | Max |                   |
| 1.0                | 3.09    | 10.0    | 1.5     | 2.2 | 4.7 | 20 - 68           |
| 1.05               | 3.74    | 10.0    | 1.5     | 2.2 | 4.7 | 20 - 68           |
| 1.2                | 5.76    | 10.0    | 1.5     | 2.2 | 4.7 | 20 - 68           |
| 1.5                | 9.53    | 10.0    | 1.5     | 2.2 | 4.7 | 20 - 68           |
| 1.8                | 13.7    | 10.0    | 1.5     | 2.2 | 4.7 | 20 - 68           |
| 2.5                | 22.6    | 10.0    | 2.2     | 3.3 | 4.7 | 20 - 68           |
| 3.3                | 33.2    | 10.0    | 2.2     | 3.3 | 4.7 | 20 - 68           |
| 5.0                | 54.9    | 10.0    | 3.3     | 4.7 | 4.7 | 20 - 68           |
| 6.5                | 75.0    | 10.0    | 3.3     | 4.7 | 4.7 | 20 - 68           |

## 4 Test Setup and Results

This section describes how to properly connect, set up, and use the TPS563210EVM-663. The section also includes test results typical for the evaluation modules and efficiency, output load regulation, output line regulation, load transient response, output voltage ripple, input voltage ripple, start-up, and switching frequency.

### 4.1 Input/Output Connections

The TPS563210EVM-663 is provided with input/output connectors and test points as shown in [Table 4](#). A power supply capable of supplying 3 A must be connected to J1 through a pair of 20-AWG wires. The load must be connected to J2 through a pair of 20-AWG wires. The maximum load current capability is 3 A. Wire lengths must be minimized to reduce losses in the wires. Test point TP1 provides a place to monitor the  $V_{IN}$  input voltages with TP2 providing a convenient ground reference. TP7 is used to monitor the output voltage with TP8 as the ground reference.

**Table 4. Connection and Test Points**

| Reference Designator | Function  |
|----------------------|---|
| J1                   | $V_{IN}$ (see <a href="#">Table 1</a> for $V_{IN}$ range)               |
| J2                   | $V_{OUT}$ , 1.05 V at 3-A maximum                                       |
| JP1                  | EN control. Shunt EN to GND to disable, shunt EN to $V_{IN}$ to enable. |
| TP1                  | $V_{IN}$ positive monitor point   |
| TP2                  | GND monitor test point  |
| TP3                  | EN test point   |
| TP4                  | Switch node test point  |
| TP5                  | Test point for loop response measurements                               |
| TP6                  | $V_{OUT}$ positive monitor point  |
| TP7                  | GND monitor test point  |

### 4.2 Start-Up Procedure

1. Ensure that the jumper at JP1 (Enable control) pins 1 and 2 are covered to shunt EN to GND, disabling the output.
2. Apply appropriate  $V_{IN}$  voltage to VI (J1-2) and GND (J1-1).
3. Move the jumper at JP1 (Enable control) from pins 1 and 2 (EN and GND), to pins 2 and 3 (EN and  $V_{IN}$ ) enabling the output.

### 4.3 Efficiency

Figure 1 shows the efficiency for the TPS563210EVM-663 at an ambient temperature of 25°C.




Figure 1. TPS563210EVM-663 Efficiency

Figure 2 shows the efficiency at light loads for the TPS563210EVM-663 at an ambient temperature of 25°C.






Figure 2. TPS563210EVM-663 Light Load Efficiency

#### 4.4 Load Regulation

The load regulation for the TPS563210EVM-663 is shown in [Figure 3](#) and [Figure 4](#).




**Figure 3. TPS563210EVM-663 Load Regulation, 5 V Input**



**Figure 4. TPS563210EVM-663 Load Regulation, 12 V Input**

### 4.5 Line Regulation


The line regulation for the TPS563210EVM-663 is shown in [Figure 5](#).



**Figure 5. TPS563210EVM-663 Line Regulation**

### 4.6 Load Transient Response


The TPS563210EVM-663 response to load transient is shown in [Figure 6](#). The current steps and slew rates are indicated in the figures. Total peak-to-peak voltage variation is as shown.




**Figure 6. TPS563210EVM-663 Load Transient Response, 25% to 75% Load Step**

## 4.7 Output Voltage Ripple

The TPS563210EVM-663 output voltage ripple is shown in [Figure 7](#), [Figure 8](#), and [Figure 9](#). The output currents are as indicated.



**Figure 7. TPS563210EVM-663 Output Voltage Ripple,  $I_{\text{OUT}} = 3 \text{ A}$**



**Figure 8. TPS563210EVM-663 Output Voltage Ripple,  $I_{\text{OUT}} = 300 \text{ mA}$**






Figure 9. TPS563210EVM-663 Output Voltage Ripple,  $I_{OUT} = 0 \text{ mA}$

#### 4.8 Input Voltage Ripple

The TPS563210EVM-663 input voltage ripple is shown in Figure 10. The output current is as indicated.





Figure 10. TPS563210EVM-663 Input Voltage Ripple,  $I_{OUT} = 3 \text{ A}$


## 4.9 Start-Up

The TPS563210EVM-663 start-up waveform relative to  $V_{IN}$  is shown in Figure 11. Load = 1  $\Omega$  resistive.



**Figure 11. TPS563210EVM-663 Start-Up Relative to  $V_{IN}$**

The TPS563210EVM-663 start-up waveform relative to enable (EN) is shown in Figure 12. Load = 1  $\Omega$  resistive.



**Figure 12. TPS563210EVM-663 Start-Up Relative to EN**

### 4.10 Shut-Down

The TPS563210EVM-663 shut-down waveform relative to  $V_{IN}$  is shown in Figure 13. Load = 1  $\Omega$  resistive.




Figure 13. TPS563210EVM-663 Shut-Down Relative to  $V_{IN}$

The TPS563210EVM-663 shut-down waveform relative to EN is shown in Figure 14. Load = 1  $\Omega$  resistive.




Figure 14. TPS563210EVM-663 Shut-Down Relative to EN

## 5 Board Layout

This section provides a description of the TPS563210EVM-663, board layout, and layer illustrations.

### 5.1 Layout

The board layout for the TPS563210EVM-663 is shown in [Figure 15](#), [Figure 16](#), and [Figure 17](#). The top layer contains the main power traces for VIN, VOUT, and ground. Also on the top layer are connections for the pins of the TPS563210 and a large area filled with ground. Most of the signal traces are also located on the top side. The input decoupling capacitors, C1, C2, and C3 are located as close to the IC as possible. The input and output connectors, test points, and all of the components are located on the top side. The bottom layer is a ground plane along with the switching node copper fill, signal ground copper fill and the feed back trace from the point of regulation to the top of the resistor divider network.




Figure 15. Top Assembly




Figure 16. Top Layer




Figure 17. Bottom Layer

## 6 Schematic, Bill of Materials, and Reference

### 6.1 Schematic

Figure 18 is the schematic for the TPS563210EVM-663.




Figure 18. TPS563210EVM-663 Schematic Diagram

## 6.2 Bill of Materials

Table 5 lists the BOM for the EVM.

**Table 5. Bill of Materials**

| Designator     | Quantity | Value  | Description  | Package Reference          | Part Number        | Manufacturer                |
|----------------|----------|--------|--|----------------------------|--------------------|-----------------------------|
| !PCB1          | 1        |        | Printed Circuit Board  |                            | PWR663             | Any                         |
| C1, C5         | 2        | 0.1uF  | CAP, CERM, 0.1uF, 25V, +/-10%, X5R, 0603                                       | 0603                       | GRM188R61E104KA01D | MuRata                      |
| C2, C3         | 2        | 10uF   | CAP, CERM, 10uF, 25V, +/-10%, X5R, 1210  | 1210                       | GRM32DR61E106KA12L | MuRata                      |
| C4             | 1        | 8200pF | CAP, CERM, 8200pF, 25V, +/-10%, X7R, 0603                                      | 0603                       | GRM188R71E822KA01D | MuRata                      |
| C6, C7, C8     | 3        | 22uF   | CAP, CERM, 22uF, 10V, +/-10%, X7R, 1206  | 1206                       | GRM31CR71A226KE15L | MuRata                      |
| J1, J2         | 2        |        | Terminal Block, 6A, 3.5mm Pitch, 2-Pos, TH                                     | 7.0x8.2x6.5mm              | ED555/2DS          | On-Shore Technology         |
| JP1            | 1        |        | Header, 100mil, 3x1, Tin, TH   | Header, 3 PIN, 100mil, Tin | PEC03SAAN          | Sullins Connector Solutions |
| JP2            | 1        |        | Header, 100mil, 2x1, Tin, TH   | Header, 2 PIN, 100mil, Tin | PEC02SAAN          | Sullins Connector Solutions |
| L1             | 1        | 1.5uH  | Inductor, Shielded Drum Core, Superflux, 1.5uH, 11A, 0.0078 ohm, SMD           | WE-HC4                     | 744311150          | Würth Elektronik eiSos      |
| LBL1           | 1        |        | Thermal Transfer Printable Labels, 1.250" W x 0.250" H - 10,000 per roll       | PCB Label 1.25"H x 0.250"W | THT-13-457-10      | Brady                       |
| R1             | 1        | 3.74k  | RES, 3.74k ohm, 1%, 0.1W, 0603   | 0603                       | CRCW06033K74FKEA   | Vishay-Dale                 |
| R2, R4         | 2        | 10.0k  | RES, 10.0k ohm, 1%, 0.1W, 0603   | 0603                       | CRCW060310K0FKEA   | Vishay-Dale                 |
| R3             | 1        | 0      | RES, 0 ohm, 5%, 0.1W, 0603   | 0603                       | ERJ-3GEY0R00V      | Panasonic                   |
| R5             | 1        | 100k   | RES, 100k ohm, 1%, 0.1W, 0603  | 0603                       | CRCW0603100KFKEA   | Vishay-Dale                 |
| SH-JP1, SH-JP2 | 2        | 1x2    | Shunt, 100mil, Gold plated, Black  | Shunt                      | 969102-0000-DA     | 3M                          |
| TP1, TP7       | 2        | Red    | Test Point, Miniature, Red, TH   | Red Miniature Testpoint    | 5000               | Keystone                    |
| TP2, TP8       | 2        | Black  | Test Point, Miniature, Black, TH   | Black Miniature Testpoint  | 5001               | Keystone                    |
| TP3, TP5, TP6  | 3        | White  | Test Point, Miniature, White, TH   | White Miniature Testpoint  | 5002               | Keystone                    |
| TP4            | 1        | Yellow | Test Point, Miniature, Yellow, TH  | Yellow Miniature Testpoint | 5004               | Keystone                    |
| U1             | 1        |        | TPS563210 4.5V to 17 V Input, Synchronous Step-Down Voltage Regulator DDF0008A | DDF0008A                   | TPS563210DDF       | Texas Instruments           |

### 6.3 Reference

1. *TPS56x210 4.5 V to 17 V Input, 2-A/3-A Synchronous Step-Down Voltage Regulator in SOT-23 data sheet* ([SLVSCM6](#))

## STANDARD TERMS AND CONDITIONS FOR EVALUATION MODULES

1. *Delivery:* TI delivers TI evaluation boards, kits, or modules, including any accompanying demonstration software, components, or documentation (collectively, an "EVM" or "EVMs") to the User ("User") in accordance with the terms and conditions set forth herein. Acceptance of the EVM is expressly subject to the following terms and conditions.
  - 1.1 EVMs are intended solely for product or software developers for use in a research and development setting to facilitate feasibility evaluation, experimentation, or scientific analysis of TI semiconductors products. EVMs have no direct function and are not finished products. EVMs shall not be directly or indirectly assembled as a part or subassembly in any finished product. For clarification, any software or software tools provided with the EVM ("Software") shall not be subject to the terms and conditions set forth herein but rather shall be subject to the applicable terms and conditions that accompany such Software
  - 1.2 EVMs are not intended for consumer or household use. EVMs may not be sold, sublicensed, leased, rented, loaned, assigned, or otherwise distributed for commercial purposes by Users, in whole or in part, or used in any finished product or production system.
2. *Limited Warranty and Related Remedies/Disclaimers:*
  - 2.1 These terms and conditions do not apply to Software. The warranty, if any, for Software is covered in the applicable Software License Agreement.
  - 2.2 TI warrants that the TI EVM will conform to TI's published specifications for ninety (90) days after the date TI delivers such EVM to User. Notwithstanding the foregoing, TI shall not be liable for any defects that are caused by neglect, misuse or mistreatment by an entity other than TI, including improper installation or testing, or for any EVMs that have been altered or modified in any way by an entity other than TI. Moreover, TI shall not be liable for any defects that result from User's design, specifications or instructions for such EVMs. Testing and other quality control techniques are used to the extent TI deems necessary or as mandated by government requirements. TI does not test all parameters of each EVM.
  - 2.3 If any EVM fails to conform to the warranty set forth above, TI's sole liability shall be at its option to repair or replace such EVM, or credit User's account for such EVM. TI's liability under this warranty shall be limited to EVMs that are returned during the warranty period to the address designated by TI and that are determined by TI not to conform to such warranty. If TI elects to repair or replace such EVM, TI shall have a reasonable time to repair such EVM or provide replacements. Repaired EVMs shall be warranted for the remainder of the original warranty period. Replaced EVMs shall be warranted for a new full ninety (90) day warranty period.
3. *Regulatory Notices:*
  - 3.1 *United States*
    - 3.1.1 *Notice applicable to EVMs not FCC-Approved:*

This kit is designed to allow product developers to evaluate electronic components, circuitry, or software associated with the kit to determine whether to incorporate such items in a finished product and software developers to write software applications for use with the end product. This kit is not a finished product and when assembled may not be resold or otherwise marketed unless all required FCC equipment authorizations are first obtained. Operation is subject to the condition that this product not cause harmful interference to licensed radio stations and that this product accept harmful interference. Unless the assembled kit is designed to operate under part 15, part 18 or part 95 of this chapter, the operator of the kit must operate under the authority of an FCC license holder or must secure an experimental authorization under part 5 of this chapter.
    - 3.1.2 *For EVMs annotated as FCC – FEDERAL COMMUNICATIONS COMMISSION Part 15 Compliant:*

### CAUTION

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### FCC Interference Statement for Class A EVM devices

*NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.*



## **FCC Interference Statement for Class B EVM devices**

*NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:*

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### 3.2 Canada

3.2.1 For EVMs issued with an Industry Canada Certificate of Conformance to RSS-210

#### **Concerning EVMs Including Radio Transmitters:**

This device complies with Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

#### **Concernant les EVMs avec appareils radio:**

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes: (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

#### **Concerning EVMs Including Detachable Antennas:**

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication. This radio transmitter has been approved by Industry Canada to operate with the antenna types listed in the user guide with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

#### **Concernant les EVMs avec antennes détachables**

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante. Le présent émetteur radio a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés dans le manuel d'usage et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

### 3.3 Japan

3.3.1 *Notice for EVMs delivered in Japan:* Please see [http://www.tij.co.jp/lstds/ti\\_ja/general/eStore/notice\\_01.page](http://www.tij.co.jp/lstds/ti_ja/general/eStore/notice_01.page) 日本国内に輸入される評価用キット、ボードについては、次のところをご覧ください。  
[http://www.tij.co.jp/lstds/ti\\_ja/general/eStore/notice\\_01.page](http://www.tij.co.jp/lstds/ti_ja/general/eStore/notice_01.page)

3.3.2 *Notice for Users of EVMs Considered "Radio Frequency Products" in Japan:* EVMs entering Japan are NOT certified by TI as conforming to Technical Regulations of Radio Law of Japan.

If User uses EVMs in Japan, User is required by Radio Law of Japan to follow the instructions below with respect to EVMs:

1. Use EVMs in a shielded room or any other test facility as defined in the notification #173 issued by Ministry of Internal Affairs and Communications on March 28, 2006, based on Sub-section 1.1 of Article 6 of the Ministry's Rule for Enforcement of Radio Law of Japan,
2. Use EVMs only after User obtains the license of Test Radio Station as provided in Radio Law of Japan with respect to EVMs, or
3. Use of EVMs only after User obtains the Technical Regulations Conformity Certification as provided in Radio Law of Japan with respect to EVMs. Also, do not transfer EVMs, unless User gives the same notice above to the transferee. Please note that if User does not follow the instructions above, User will be subject to penalties of Radio Law of Japan.

**【無線電波を送信する製品の開発キットをお使いになる際の注意事項】**

本開発キットは技術基準適合証明を受けておりません。

本製品のご使用に際しては、電波法遵守のため、以下のいずれかの措置を取っていただく必要がありますのでご注意ください。

1. 電波法施行規則第6条第1項第1号に基づく平成18年3月28日総務省告示第173号で定められた電波暗室等の試験設備でご使用いただく。
2. 実験局の免許を取得後ご使用いただく。
3. 技術基準適合証明を取得後ご使用いただく。

なお、本製品は、上記の「ご使用にあたっての注意」を譲渡先、移転先に通知しない限り、譲渡、移転できないものとします。

上記を遵守頂けない場合は、電波法の罰則が適用される可能性があることをご留意ください。

日本テキサス・インスツルメンツ株式会社

東京都新宿区西新宿 6 丁目 2 4 番 1 号

西新宿三井ビル

3.3.3 *Notice for EVMs for Power Line Communication:* Please see [http://www.tij.co.jp/llds/ti\\_ja/general/eStore/notice\\_02.page](http://www.tij.co.jp/llds/ti_ja/general/eStore/notice_02.page)

電力線搬送波通信についての開発キットをお使いになる際の注意事項については、次のところをご覧ください。[http://www.tij.co.jp/llds/ti\\_ja/general/eStore/notice\\_02.page](http://www.tij.co.jp/llds/ti_ja/general/eStore/notice_02.page)

4 *EVM Use Restrictions and Warnings:*

4.1 EVMS ARE NOT FOR USE IN FUNCTIONAL SAFETY AND/OR SAFETY CRITICAL EVALUATIONS, INCLUDING BUT NOT LIMITED TO EVALUATIONS OF LIFE SUPPORT APPLICATIONS.

4.2 User must read and apply the user guide and other available documentation provided by TI regarding the EVM prior to handling or using the EVM, including without limitation any warning or restriction notices. The notices contain important safety information related to, for example, temperatures and voltages.

4.3 *Safety-Related Warnings and Restrictions:*

4.3.1 User shall operate the EVM within TI's recommended specifications and environmental considerations stated in the user guide, other available documentation provided by TI, and any other applicable requirements and employ reasonable and customary safeguards. Exceeding the specified performance ratings and specifications (including but not limited to input and output voltage, current, power, and environmental ranges) for the EVM may cause personal injury or death, or property damage. If there are questions concerning performance ratings and specifications, User should contact a TI field representative prior to connecting interface electronics including input power and intended loads. Any loads applied outside of the specified output range may also result in unintended and/or inaccurate operation and/or possible permanent damage to the EVM and/or interface electronics. Please consult the EVM user guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative. During normal operation, even with the inputs and outputs kept within the specified allowable ranges, some circuit components may have elevated case temperatures. These components include but are not limited to linear regulators, switching transistors, pass transistors, current sense resistors, and heat sinks, which can be identified using the information in the associated documentation. When working with the EVM, please be aware that the EVM may become very warm.

4.3.2 EVMs are intended solely for use by technically qualified, professional electronics experts who are familiar with the dangers and application risks associated with handling electrical mechanical components, systems, and subsystems. User assumes all responsibility and liability for proper and safe handling and use of the EVM by User or its employees, affiliates, contractors or designees. User assumes all responsibility and liability to ensure that any interfaces (electronic and/or mechanical) between the EVM and any human body are designed with suitable isolation and means to safely limit accessible leakage currents to minimize the risk of electrical shock hazard. User assumes all responsibility and liability for any improper or unsafe handling or use of the EVM by User or its employees, affiliates, contractors or designees.

4.4 User assumes all responsibility and liability to determine whether the EVM is subject to any applicable international, federal, state, or local laws and regulations related to User's handling and use of the EVM and, if applicable, User assumes all responsibility and liability for compliance in all respects with such laws and regulations. User assumes all responsibility and liability for proper disposal and recycling of the EVM consistent with all applicable international, federal, state, and local requirements.

5. *Accuracy of Information:* To the extent TI provides information on the availability and function of EVMs, TI attempts to be as accurate as possible. However, TI does not warrant the accuracy of EVM descriptions, EVM availability or other information on its websites as accurate, complete, reliable, current, or error-free.

6. *Disclaimers:*
- 6.1 EXCEPT AS SET FORTH ABOVE, EVMS AND ANY WRITTEN DESIGN MATERIALS PROVIDED WITH THE EVM (AND THE DESIGN OF THE EVM ITSELF) ARE PROVIDED "AS IS" AND "WITH ALL FAULTS." TI DISCLAIMS ALL OTHER WARRANTIES, EXPRESS OR IMPLIED, REGARDING SUCH ITEMS, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY THIRD PARTY PATENTS, COPYRIGHTS, TRADE SECRETS OR OTHER INTELLECTUAL PROPERTY RIGHTS.
- 6.2 EXCEPT FOR THE LIMITED RIGHT TO USE THE EVM SET FORTH HEREIN, NOTHING IN THESE TERMS AND CONDITIONS SHALL BE CONSTRUED AS GRANTING OR CONFERRING ANY RIGHTS BY LICENSE, PATENT, OR ANY OTHER INDUSTRIAL OR INTELLECTUAL PROPERTY RIGHT OF TI, ITS SUPPLIERS/LICENSORS OR ANY OTHER THIRD PARTY, TO USE THE EVM IN ANY FINISHED END-USER OR READY-TO-USE FINAL PRODUCT, OR FOR ANY INVENTION, DISCOVERY OR IMPROVEMENT MADE, CONCEIVED OR ACQUIRED PRIOR TO OR AFTER DELIVERY OF THE EVM.
7. *USER'S INDEMNITY OBLIGATIONS AND REPRESENTATIONS.* USER WILL DEFEND, INDEMNIFY AND HOLD TI, ITS LICENSORS AND THEIR REPRESENTATIVES HARMLESS FROM AND AGAINST ANY AND ALL CLAIMS, DAMAGES, LOSSES, EXPENSES, COSTS AND LIABILITIES (COLLECTIVELY, "CLAIMS") ARISING OUT OF OR IN CONNECTION WITH ANY HANDLING OR USE OF THE EVM THAT IS NOT IN ACCORDANCE WITH THESE TERMS AND CONDITIONS. THIS OBLIGATION SHALL APPLY WHETHER CLAIMS ARISE UNDER STATUTE, REGULATION, OR THE LAW OF TORT, CONTRACT OR ANY OTHER LEGAL THEORY, AND EVEN IF THE EVM FAILS TO PERFORM AS DESCRIBED OR EXPECTED.
8. *Limitations on Damages and Liability:*
- 8.1 *General Limitations.* IN NO EVENT SHALL TI BE LIABLE FOR ANY SPECIAL, COLLATERAL, INDIRECT, PUNITIVE, INCIDENTAL, CONSEQUENTIAL, OR EXEMPLARY DAMAGES IN CONNECTION WITH OR ARISING OUT OF THESE TERMS AND CONDITIONS OR THE USE OF THE EVMS PROVIDED HEREUNDER, REGARDLESS OF WHETHER TI HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. EXCLUDED DAMAGES INCLUDE, BUT ARE NOT LIMITED TO, COST OF REMOVAL OR REINSTALLATION, ANCILLARY COSTS TO THE PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES, RETESTING, OUTSIDE COMPUTER TIME, LABOR COSTS, LOSS OF GOODWILL, LOSS OF PROFITS, LOSS OF SAVINGS, LOSS OF USE, LOSS OF DATA, OR BUSINESS INTERRUPTION. NO CLAIM, SUIT OR ACTION SHALL BE BROUGHT AGAINST TI MORE THAN ONE YEAR AFTER THE RELATED CAUSE OF ACTION HAS OCCURRED.
- 8.2 *Specific Limitations.* IN NO EVENT SHALL TI'S AGGREGATE LIABILITY FROM ANY WARRANTY OR OTHER OBLIGATION ARISING OUT OF OR IN CONNECTION WITH THESE TERMS AND CONDITIONS, OR ANY USE OF ANY TI EVM PROVIDED HEREUNDER, EXCEED THE TOTAL AMOUNT PAID TO TI FOR THE PARTICULAR UNITS SOLD UNDER THESE TERMS AND CONDITIONS WITH RESPECT TO WHICH LOSSES OR DAMAGES ARE CLAIMED. THE EXISTENCE OF MORE THAN ONE CLAIM AGAINST THE PARTICULAR UNITS SOLD TO USER UNDER THESE TERMS AND CONDITIONS SHALL NOT ENLARGE OR EXTEND THIS LIMIT.
9. *Return Policy.* Except as otherwise provided, TI does not offer any refunds, returns, or exchanges. Furthermore, no return of EVM(s) will be accepted if the package has been opened and no return of the EVM(s) will be accepted if they are damaged or otherwise not in a resalable condition. If User feels it has been incorrectly charged for the EVM(s) it ordered or that delivery violates the applicable order, User should contact TI. All refunds will be made in full within thirty (30) working days from the return of the components(s), excluding any postage or packaging costs.
10. *Governing Law:* These terms and conditions shall be governed by and interpreted in accordance with the laws of the State of Texas, without reference to conflict-of-laws principles. User agrees that non-exclusive jurisdiction for any dispute arising out of or relating to these terms and conditions lies within courts located in the State of Texas and consents to venue in Dallas County, Texas. Notwithstanding the foregoing, any judgment may be enforced in any United States or foreign court, and TI may seek injunctive relief in any United States or foreign court.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2014, Texas Instruments Incorporated

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

|                              |  |
|------------------------------|--|
| Audio                        | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers                   | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters              | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products                | <a href="http://www.dlp.com">www.dlp.com</a>   |
| DSP                          | <a href="http://dsp.ti.com">dsp.ti.com</a>   |
| Clocks and Timers            | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface                    | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                        | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt                   | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers             | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                         | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Applications Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity        | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |  |
|-------------------------------|--|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)