

## WebSensor - remote thermometer with Ethernet interface

code: T4511

Ambient temperature t-line Web sensor for Pt1000 sensor. Remote alarm.  
Web Sensor for external Pt1000 temperature probe.

[Easy wireless communication using Web Sensor and optional Wireless TP-LINK router.](#)



### Technical data

|  |                                     |
|--|-------------------------------------|
| TEMPERATURE SENSOR - external probe Pt1000 |                                     |
| Measuring range                            | -200 to +600 °C                     |
| Accuracy                                   | ±0.2°C                              |
| Resolution                                 | 0.1 °C                              |
| GENERAL TECHNICAL DATA                     |                                     |
| Operating temperature                      | -30 to +80 °C                       |
| Channels                                   | 1x external temperature probe       |
| Output                                     | Ethernet                            |
| Measuring interval                         | 2 s                                 |
| Available temperature units                | degrees Celsius, degrees Fahrenheit |
| Communication protocol                     | WWW, ModbusTCP, SNMPv1, SOAP, XML   |
| Alarm protocols                            | E-mail, SNMP Trap, Syslog           |
| Power                                      | 9-30 Vdc                            |
| Protection class                           | IP30                                |
| Dimensions                                 | 88,5 x 94 x 39,5 mm                 |
| Weight                                     | approx. 145 g                       |
| Warranty                                   | 3 years                             |