### GENERAL INFORMATION

230PC pressure sensors are four-active-element piezoresistive bridges. When pressure is applied, an output voltage proportional to pressure is produced.


Gage pressure is measured with respect to atmospheric (room) pressure reference. The output increases for pressure above atmospheric, and decreases for pressure below. The remote atmospheric pressure reference is inside the termination cable, reducing the chance of contaminants entering the sensor enclosure.

#### **MEASURAND**

230PC series pressure sensors are compatible with most input media, but are specifically restricted by those which will not attack silicon, glass, 300 series stainless steel, or urethane based epoxy.


#### **MOUNTING DIMENSIONS**

(For reference only)



#### LEADWIRE COLOR CODE


- 1 Red, Vs
- 2 White, Output A
- 3 Black, Ground
- 4 Green, Output B




#### **ELECTRICAL CONNECTIONS**

Voltage 234/236PC

Current 234PC





#### **NOTES:**

- 1. The circled numbers refer to sensor termination.
- 2. Vo increases with pressure difference.
- 3. Vo = V2 V4 (referenced to point 3).
- 4. Current excitation (234PC) provides reduced sensitivity variation with temperature.

#### WARRANTY/REMEDY

Seller warrants its products to be free from defects in design, material and workmanship under normal use and service. Seller will repair or replace without charge any such product it finds to be so defective on its return to Seller within 18 months after date of shipment by Seller. The foregoing is in lieu of all other expressed or implied warranties (except of title) including those of merchantability and fitness for a particular purpose. The foregoing is also purchaser's sole remedy and is in lieu of all other guarantees, obligations, or liabilities or any consequential, incidental, or punitive damages attributable to negligence or strict liability, all by way of example.

# MICRO SWITCH a Honeywell Division

## 230PC Stainless Steel Housed Pressure Sensors

### 230PC SPECIFICATIONS at $10.0 \pm 0.01$ VDC Excitation, 25°C (unless otherwise noted)

	Pressure					
Parameter	Range	Type*	Min.	Тур.	Max.	Units
F.S.O. (Full Scale Output)**	0-5 psi	234 236	80 48	115 50	150 52	m V
	0-15 psi	234 236	175 98.5	250 100	325 101.5	m V
	0-30 psi	234 236	110 78	195 80	280 82	m V
	0-60 psi	234 236	90 58	135 60	180 62	m V
	0-100 psi	234 236	150 98	225 100	300 102	m V
	0-150 psi	234 236	90 58	127.5 60	165 62	m V
Null Offset	AII	234 236	-40	0 0	+40 +2	m V
Recommended Excitation Voltage Current Voltage	AII	234 234 236		10 2 10	12 2.4 16	VDC mA VDC
Input Resistance	AII	234 236		5 K 6.8K		Ohms
Overpressure	0-5 psi 0-15 psi 0-30 psi 0-60 psi 0-100 psi 0-150 psi	AII			2 0 45 6 0 100 150 225	psi
Operating Temperature	AII	AII	-30°C to + 70°C (-22°F to + 158°F)			
Storage Temperature	AII	AII	-40°C to + 105°C (-40°F to + 221°F)			

<sup>\* 234</sup>PC - basic sensor

While we provide application assistance on MICRO SWITCH products, personally and through our literature, it is up to the customer to determine the suitability of the product in the application.

## MICRO SWITCH a Honeywell Division

<sup>236</sup>PC - trimmed plus thermistor (low sensitivity shift with temperature)

<sup>\*\*</sup> F.S.O. is the algebraic difference between end points (output at minimum and maximum pressure)