

MACD-14 14mm Close-Differential Reed Switch




Agency Approvals

Agency	Agency File Number	Ampere-Turns Range	
c FL [°] us	E47258 E471070	10-30 AT	
Æx>	DEMKO 14 ATEX 1393U	10-30 AT	

Note: Contact Littelfuse for specific agency approval ratings.

Dimensions

Dimensions in mm (inch)



Electrical Ratings

Description

The MACD-14 reed switch is a close-differential, sub-miniature, normally open switch with a 14.00mm long x 2.28mm diameter (0.551" x 0.090") glass envelope, capable of switching 200Vdc at 10W.

This reed switch is also available in a surface mount version, MASM-14. It has a high insulation resistance of 10¹⁰ ohms minimum and contact resistance less than 100 milli-ohms. Both reed switches are intended for use in applications that require low hysteresis between Pull-In and Drop-Out values.

Features

- · Low close/open hysteresis (close differential)
- Normally open switch
- Capable of switching
- 200Vdc or 0.5A at up to 10W • UL Recognized for the US and
- Canadian Markets per UL 508 and CSA C22.2 No. 14-10.

Benefits

· Hermetically sealed switch contacts are not affected by and have no effect on their external environment

Applications

- Position Sensing
- Level Sensing

· Security

- Office Equipment

Switch Type

Home Appliances

Contact Form	A (SPST-NO)
Materials	Body: Glass Leads: Tin-plated Ni-Fe wire

Note: SPST-NO = Single-pole, single-throw, normally open

Contact Rating ¹		W/VA - max.	10
Voltage ³	Switching ² Breakdown ⁴	Vdc - max. Vac - max. Vdc - min.	200 140 200
Current ³	Switching ² Carry	Adc - max. Aac - max. Adc - max.	0.50 0.35 1.00
Resistance	Contact, Initial Insulation	Ω - max. Ω - min.	0.100 10 ¹⁰
Capacitance	Contact	pF - typ.	0.3
Temperature	Operating Storage ⁵	°C °C	-40 to +125 -65 to +125

Notes:

1. Contact rating - Product of the switching voltage and current should never exceed the wattage rating. Contact Littelfuse for additional load/life information

2. When switching inductive and/or capacitive loads, the effects of transient voltages and/or currents should be considered. Refer to Application Notes AN108A and AN107 for details.

3. Electrical Load Life Expectancy - Contact Littelfuse with voltage and current values along with type of load.

4. Breakdown Voltage - per MIL-STD-202, Method 301.

5. Storage Temperature - Long time exposure at elevated temperature may degrade solderability of the leads

• UL Recognized for use in Class I,

Hazardous Locations.

IIC Gc.

Division 2, Groups A, B, C and D

• Evaluated as an ATEX Component

for use in Potentially Explosive

· Zero operating power required for

· Excellent for switching micro-

controller logic level loads

Atmospheres. Marked II 3 G Ex nC

and Class I, Zone 2, AEx/Ex nC IIC

contact closure

Industrial Controls

MACD-14 14mm Close-Differential Reed Switch

Product Characteristics

Operating Characteristics						
Operate Time ¹		0.6ms - max.				
Release Time ¹		0.20ms - max.				
Shock ²	11ms 1/2 sine wave	100G - max.				
Vibration ²	50-2000 Hertz	30G - max.				
Resonant Frequency		5.3kHz - typ.				
Magnetic Characteristics						
Pull-In Range ³	Ampere Turns	10-30				
Rating Sensitivity ⁴	Ampere Turns	20				
Test Coil		L4989				

Notes:

1. Operate (including bounce)/Release Time - per EIA/NARM RS-421-A, diode suppressed coil (Coil II).


2. Shock and Vibration - per EIA/NARM RS-421-A and MIL-STD-202.

3. Pull-In Range - Contact Littelfuse for narrower AT ranges available.

4. Rating Sensitivity - The value at which contact ratings and operating characteristics are determined. Derating may be required below this value.


5. Custom modifications of forming and/or cutting of reed switches are available. Please contact Littelfuse.

Drop-Out vs. Pull-In Chart



Note: Chart represents the range of Drop-Out, min to max for a given Pull-In value.

Part Numbering System



Note: These AT values are the before-modification values of the bare reed switch.

Packaging

Packaging Option	Packaging Specification	Quantity	Quantity & Packaging Code	Taping Width
Bulk	Bulk	1000	N/A	N/A

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at: www.littelfuse.com/disclaimer-electronics.