Axial Lead Fuse, 6.3x32 mm, 440 - 500 VAC, 400 - 500 VDC, 1-8 A, High Breaking Capacity ≥1500 A





UL 248-14 · 440 - 50	0VAC · Quick-Acting F	See below: Approvals and Compliances					
<ul> <li>Description</li> <li>6.3 x 32 mm fuses for primary protection</li> <li>10 rated currents from 1 A to 8 A</li> <li>Unique Selling Proposition</li> <li>High rated voltages up to 500 VAC / DC</li> <li>High breaking capacity ≥ 1500 A</li> </ul>		Applications - 3-phase applications - DC applications - Power supplies - Frequency converter - Power electronics					
	Figh broaking deputity = 1000 / 1		References Packaging Details				
		Weblinks pdf data sheet, html datasheet, General Product Information, Packagin details, Distributor-Stock-Check, Detailed request for product					
Technical Data							
Rated Voltage	440 - 500 VAC, 63 - 500 VDC	Solderability	235 °C / 2 sec acc. to IEC 60068-2-20				
Rated current	1 - 8A	Resistance to Soldering Heat	260°C / 10 sec acc. to IEC 60068-2-58				
Breaking Capacity	1500A - 20kA						
Characteristic	Quick-Acting F						
Mounting	Solder, THT						

Climatic Category Material: Tube

Material: Endcaps

Unit Weight

Material: Axial Leads

Storage Conditions

Product Marking

Admissible Ambient Air Temp. -40 °C to 85 °C

40/085/21 acc. to IEC 60068-1

Nickel-Plated Copper Alloy

0°C to 60°C, max. 70% r.h.

**(D)**, Type, Rated current, Rated Voltage, Characteristic, Breaking capacity, Ap-

**Tin-Plated Copper** 

Ceramics

3.54 g

provals

Detailed information on product approvals, code requirements, usage instructions and detailed test conditions can be looked up in Details about Approvals

SCHURTER products are designed for use in industrial environments. They have approvals from independent testing bodies according to national and international standards. Products with specific characteristics and requirements such as required in the automotive sector according to IATF 16949, medical technology according to ISO 13485 or in the aerospace industry can be offered exclusively with customer-specific, individual agreements by SCHURTER.

### Approvals

The approval mark is used by the testing authorities to certify compliance with the safety requirements placed on electronic products. Approval Reference Type: SHF 6.3x32 Pigta


Approval Logo	Certificates	Certification Body	Description
c <b>FL</b> <sup>°</sup> us	UL Approvals	UL	UL File Number: E41599

# SHF 6.3x32 Pigtail

Product standards	a <b>rds</b> Is that are referenced		
Organization	Design	Standard	Description
(h)	Designed according to	UL 248-14	Low voltage fuses - Part 14: Additional fuses
CSA Group	Designed according to	CSA22.2 No. 248.14	Low-Voltage Fuses - Part 14: Supplemental Fuses
Application star	ndards ards where the product can be used	1	
Organization	Design	Standard	Description
IEC	Designed for applications acc.	IEC/UL 62368-1	IEC 62368-1 includes the basic requirements for safety of audio, video, information technology and office equipment.
Compliances			
The product comp	blies with following Guide Lines		
Identification	Details	Initiator	Description
CE	CE declaration of conformity	SCHURTER AG	The CE marking declares that the product complies with the applicable requirements laid down in the harmonisation of Community legislation on its affixing in accordance with EU Regulation 765/2008.
ROHS	RoHS	SCHURTER AG	Directive RoHS 2011/65/EU, Amendment (EU) 2015/863
<b>@</b>	China RoHS	SCHURTER AG	The law SJ / T 11363-2006 (China RoHS) has been in force since 1 March 2007. It is similar to the EU directive RoHS.
REACH	REACH	SCHURTER AG	On 1 June 2007, Regulation (EC) No 1907/2006 on the Registration, Evaluation, Authorization and Restriction of Chemicals 1 (abbreviated as "REACH") entered into force.

Dimension [mm]


6.3 mm



## $\emptyset A = 0.8 \text{ mm}$

Rated Current In         1.5 x In min.         2.1 x In max.         2.75 x In min.         2.75 x In max.         4.0 x In min.         10.0 x In min.         10.0 x In max.           1 A - 1 A         60 min         30 min         20 ms         1.5 s         8 ms         400 ms         -         20 ms           1.25 A - 8 A         60 min         30 min         100 ms         5 s         20 ms         1 s         -         50 ms	Pre-Arcing Time								
	Rated Current In	1.5 x In min.	2.1 x In max.	2.75 x In min.	2.75 x In max.	4.0 x In min.	4.0 x In max.	10.0 x In min.	10.0 x In max.
1.25 A - 8 A 60 min 30 min 100 ms 5 s 20 ms 1 s - 50 ms	1 A - 1 A	60 min	30 min	20 ms	1.5 s	8 ms	400 ms	-	20 ms
	1.25 A - 8 A	60 min	30 min	100 ms	5 s	20 ms	1 s	-	50 ms

## **Time-Current-Curves**



Multiple of Rated Current In

## **All Variants**

Rated Current [A]	Rated Voltage [VAC]	Rated Voltage [VDC]	Breaking Capacity	Voltage Drop 1.0 I <sub>n</sub> max. [mV]	Power Dissipation 1.5 I <sub>n</sub> max. [mW]	Melting I²t 10.0 I <sub>n</sub> typ. [A²s] <b>, SN</b>	Order Number
1	500	500	1)	400	1200	1.5 •	8020.5068.PT
1.25	500	500	1)	300	1300	2.9 •	8020.5069.PT
1.6	500	400	2)	300	1400	5.8 •	8020.5070.PT
2	500	400	2)	280	1700	2 •	8020.5071.PT
2.5	500	400	2)	260	2000	3.8 •	8020.5072.PT
3.15	500	400	2)	240	2300	8.6 •	8020.5073.PT
4	500	400	2)	220	2900	14.6 •	8020.5074.PT
5	500	400	2)	190	2900	33.2 •	8020.5075.PT
6.3	500	400	2)	170	3400	61.6 •	8020.5076.PT
8	500	400	2)	160	3700	120 ●	8020.5077.PT

Availability for all products can be searched real-time:https://www.schurter.com/en/Stock-Check/Stock-Check-SCHURTER

Packa	ging Unit Bulk (100 pcs.)
	20 kA @ 63 VDC
	1500 A @ 400 VDC
	10 kA @ 125 VAC, cos φ = 0.7 - 0.8
	1500 A @ 250 VAC, $\cos \varphi = 0.7 - 0.8$
2)	1500 A @ 500 VAC, $\cos \varphi = 0.99 - 1$
	20 kA @ 63 VDC
	1500 A @ 500 VDC
	10 kA @ 125 VAC, cos φ = 0.7 - 0.8
	1500 A @ 250 VAC, $\cos \varphi = 0.7 - 0.8$
1)	1500 A @ 500 VAC, $\cos \varphi = 0.99 - 1$

The specifications, descriptions and illustrations indicated in this document are based on current information. All content is subject to modifications and amendments. Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability and test each product selected for their own applications.